



Compatible  
**[SMARTBOX]**  
**<PROCESS TRACKER>**



## Classic-CLD-250

This system is also designed with the capability of handling the bare boards & PCBA into the production line, a independent bare boards destacker is equipped together with the single magazine loader, working in-line.

### FEATURES

- PCB Max : 330x250
- Panasonic PLC program control
- Loader & destacker working mode can be switched exchange.
- Selectable pitch settings
- Tower-light display for machines working status.
- Flexible platform to suit standard magazines
- Exchangeable magazine loading from the front of machine
- Stepper motorized type pusher to enhance working stability
- Pusher position adjustable to Centre for the boards
- Use the friendly touch screen panel
- Magazine infeed and outfeed are automatically driving by motor on the platform.
- Ability to handle the bare boards by destacker.
- SMEMA compatible

**<PROCESS TRACKER>**

Transfer heights	900mm+/-50mm
Transfer direction	Left to right
Lifting platform Max. weight loading	Above 100kg
Operation side	Front of machine
Fixed rail	Front of machine
Interface	SMEMA
Conveyor belts	ESD flat belt
PCB edge support	3mm
Magazine change over time	30s ( optional: 15s)
Allowable components clearance	Top 50 mm+ below 25mm
Magazine capacity	Single magazine
Safety	CE certificates
Control	PLC
Voltage	220V/ 110V , single phase, 50-60Hz
Bare boards handling capability	Total 240mm heights (0.6mm thickness)
Bare boards loading	PCB thickness: 0.6-2.5mm
Air supply	4-6 bar

## GLOBAL NETWORK

**FACTORYCENTER**  
 SEOUL - BARCELONA

**BUSINESSCENTER**  
 KOREA - MEXICO - GERMANY  
 FRANCE - SPAIN - PORTUGAL - TUNISIA

**TESTCENTER**  
 KOREA - SPAIN - FRANCE

**FACTORYCENTER**  
**BARCELONA**  
 Ctra. C-31, 148,4. Masia Les Planes, 20.  
 Camí de Les Planes. 08880 Cubelles,  
 Barcelona. Spain  
[administrative@mstechcorp.eu](mailto:administrative@mstechcorp.eu)

**BUSINESSCENTER**  
[sales@mstechcorp.eu](mailto:sales@mstechcorp.eu)  
[services@mstechcorp.eu](mailto:services@mstechcorp.eu)

